

DOMESTIC LINE

BREAKERMATIC®

ELECTRONIC PROTECTORS FOR ENTERTAINMENT EQUIPMENT

BREAKERMATIC® Televisores, allows you to protect your electronic equipment against damages that can be caused by blackouts, high or low voltage and transient surges. It has two outputs, which allow two devices to be connected simultaneously, as long as the sum of the currents or powers does not exceed the maximum allowed.

IDEAL FOR:

- Televisions and Monitors: LED, LCD, PLASMA, HDTV.
- Satellite or Cable Decoders.

FEATURES:

- Protection against: low voltage, high voltage and blackouts.
- 5 sec. waiting cycle that allows the stabilization of the electrical network.
- Suppression of transient overvoltages caused by atmospheric discharges or connection of loads.
- 4 indicator LEDs to indicate the status of the protector.
- Fully automatic operation.
- Installation: Plug and play.

**AVAILABLE MODELS / TECHNICAL SPECIFICATIONS:**

Code	Nominal Voltage	Maximum Current	Maximum Load	Pole to Ground	Disconnection Voltages	Transient Voltage Suppression	Input Connection	Output Connection	
PTV110-000EST	120VAC	10A	1250VA	YES	Low V. Cut-Off: 95 VAC ± 3% / High V. Cut-Off: 138VAC ± 3%	270V / 474J	5-15P (B)	5-15R (B)	
PTV220-000EST	220VAC	7A	1540VA	YES	Low V. Cut-Off: 200 VAC ± 3% / High V. Cut-Off: 264 VAC ± 3%	470V / 820J	5-15P (B)	5-15R (B)	
Contact Type: DRY RELAY		Ignition Delay (sec): 5		Response Time (sec): 1.5		Frecuency: 50/60Hz	Dimensions (mm): 90 x 70 x 30		Weight (g): 185